The Reciprocal Voltage-Resistance Proportionality Framework (RVRPF)

A Pedagogical Derivation and Unified Reframing of Terminal Voltage Behavior in Coupled Battery Systems

Tumaini Vedasto

O-Level Student, Rwabwere Secondary School

Email: kilinyebesa@gmail.com

Draft Date: May 2026

Abstract

This manuscript introduces the Reciprocal Voltage-Resistance Proportionality Framework (RVRPF), a novel pedagogical reframing of classical electrodynamics as applied to coupled direct-current (DC) battery systems. Historically, the analysis of charging circuits has focused heavily on absolute terminal voltages and net current flow, often obfuscating the symmetrical interplay between the supplying (source) and receiving (load) electrochemical cells. The RVRPF posits that the magnitude of voltage increase across the terminals of a receiving battery is strictly proportional to the magnitude of voltage decrease across the terminals of the supplying battery. Crucially, this proportionality constant is uniquely determined by the ratio of their respective internal resistances (denoted as the dimensionless coupling constant, κ). Grounded in the foundational tenets established by Georg Ohm, Gustav Kirchhoff, and Léon Charles Thévenin, this paper rigorously derives the RVRPF from first principles, extending the formulation into differential and integral domains to predict energy transfer over time. By unifying these classical concepts into a single, elegant proportional relationship, the framework offers profound pedagogical advantages for secondary physics education, transforming a historically procedural calculation into an intuitive, symmetry-based conceptual model.

Keywords: Electrodynamics, Internal Resistance, Kirchhoff's Laws, Proportionality Framework, Battery Charging, Secondary Education Physics, Terminal Voltage, Thevenin's Theorem.

Table of Contents

1. Introduction and Historical Background
    - 1.1 Scope and Organisation
    - 1.2 Notational Conventions
2. Foundational Physics Review
    - 2.1 Ohm's Law as the Constitutive Relation
    - 2.2 Kirchhoff's Voltage Law
    - 2.3 Kirchhoff's Current Law
    - 2.4 Thévenin's Theorem
3. The Two-Battery Coupled System — Physical Setup
    - 3.1 Sign Conventions
    - 3.2 Assumptions
4. Statement of the Reciprocal Voltage-Resistance Proportionality Framework
    - 4.1 Corollaries of the Framework
5. Derivation from First Principles
    - 5.1 Alternative Derivation via the Voltage-Divider Analogy
    - 5.2 Energy-Conservation Derivation
6. Differential Formulation
    - 6.1 Time-Varying Internal Resistances
    - 6.2 Rate of Approach to Equilibrium
7. Integration of the Framework and Energy Analysis
    - 7.1 Total Charge Transferred
    - 7.2 Energy Delivered, Stored, and Charging Efficiency
    - 7.3 Quasi-Static Time Dependence of EMFs
8. Limiting Cases and Symmetry Properties
9. Equivalence with Thévenin and Norton Representations
10. Worked Numerical Examples
11. Graphical Analysis
    - 11.1 Time-Evolution of Terminal Voltages
    - 11.2 Energy Partition Visualisation
12. Comparison with Existing Pedagogical Formulations
13. Original Contribution and Novelty Statement
    - 13.1 What is New, and What is Not

14. Pedagogical Implications for O-Level Education
    - 14.1 Identified Misconceptions Addressed
    - 14.2 Suggested Lesson Sequence
    - 14.3 Compatibility with the O-Level Syllabus
15. Discussion of Assumptions and Limitations
    - 15.1 Quantitative Estimate of Departure
    - 15.2 Extensions Outside the Domain
16. Suggested Experimental Verification Protocol
    - 16.1 Apparatus
    - 16.2 Procedure
    - 16.3 Expected Results
17. Conclusion
18. Acknowledgments
19. References (44 entries)
20. Appendix A: Detailed Algebraic Derivation
21. Appendix B: Integration Reference
22. Appendix C: Glossary of Terms
23. Suitability Checklist for the Author

5. List of Symbols and Notation

Symbol	Description	SI Unit
E_s	Electromotive Force (EMF) of the Supplying (Source) Battery	Volts (V)
E_l	Electromotive Force (EMF) of the Receiving (Load) Battery	Volts (V)
r_s	Internal Resistance of the Source Battery	Ohms (Ω)
r_l	Internal Resistance of the Load Battery	Ohms (Ω)
V_s	Terminal Voltage of the Source Battery	Volts (V)
V_l	Terminal Voltage of the Load Battery	Volts (V)
ΔV_s	Magnitude of Voltage Decrease at the Source (E_s - V_s)	Volts (V)
ΔV_l	Magnitude of Voltage Increase at the Load (V_l - E_l)	Volts (V)

κ	Dimensionless Coupling Ratio (r_1 / r_s)	Unitless
$I(t)$	Transient Charging Current at time t	Amperes (A)
Q	Total Charge Transferred	Coulombs (C)

1. Introduction and Historical Background

The study of direct current (DC) circuits and the transfer of electrical energy between chemical cells is a cornerstone of classical electromagnetism. The foundational understanding of how batteries behave under load traces its origins to the late 18th and early 19th centuries. Alessandro Volta's invention of the voltaic pile in 1800 [1] provided the first continuous source of electrical current, sparking a revolution in physics. Subsequent empirical investigations by Georg Simon Ohm, culminating in his seminal 1827 work *"Die galvanische Kette, mathematisch bearbeitet"* [2], formally linked the concepts of potential difference, electrical current, and resistance.

While Ohm's law provided the macroscopic view of single resistive elements, it was Gustav Kirchhoff in 1845 [3] who expanded these principles into network topologies. Kirchhoff's Voltage Law (KVL) and Current Law (KCL) allowed physicists to analyze closed-loop systems, including those containing multiple electromotive force (EMF) sources opposing one another—a configuration ubiquitous in battery charging circuits. In the late 19th century, Léon Charles Thévenin (1883) [4] and Hermann von Helmholtz further abstracted complex networks into simplified equivalent circuits, introducing the concept of treating a real battery as an ideal voltage source in series with an internal resistor. Helmholtz's work on the conservation of energy [26], and James Clerk Maxwell's later synthesis [12], further solidified the theoretical underpinning upon which all modern circuit analysis rests. The development of the Nernst equation by Walther Nernst in 1889 [14] additionally provided the electrochemical context for understanding the EMF of cells as a function of ion concentration and temperature, although the present framework operates at the macroscopic, lumped-parameter level rather than the electrochemical level.

The remarkable longevity of the Ohm–Kirchhoff–Thévenin trilogy is testament to its mathematical elegance and predictive power. From the design of the earliest telegraph systems by Werner von Siemens [27] to contemporary photovoltaic charge controllers and lithium-ion battery management systems [28], the same set of linear equations governs the analysis. Yet, despite more than a century and a half of refinement, the conventional presentation of two-battery charging circuits in introductory physics texts has remained essentially unchanged: a loop equation is written, an unknown current is solved, and terminal voltages are computed as a final step. The student is left with a numerical answer but rarely with an intuitive sense of the *structural symmetry* that links the two cells.

Despite these monumental advancements, classical pedagogy in secondary and introductory university physics—as seen in standard texts by Halliday, Resnick, and Walker [5], or Young and Freedman [6]—often treats the charging of a secondary cell as a purely procedural application of

KVL. Students are taught to construct the loop equation, solve for the common current I, and back-substitute to find terminal voltages. This conventional approach, while mathematically robust, frequently fails to illuminate the underlying relational symmetries between the interacting components. In particular, the fact that the *perturbations* of terminal voltage at the two cells stand in a fixed ratio—a ratio that is independent of the current, independent of the EMFs, and independent of the duration of charging—is almost never made explicit in textbook treatments. The present manuscript addresses this pedagogical gap by introducing the Reciprocal Voltage-Resistance Proportionality Framework (RVRPF).

The motivation for the present work arose from the author's own experience as an Ordinary-Level (O-Level) physics student at Rwabwere Secondary School, where the traditional Kirchhoff-based solution procedure was found to be procedurally satisfactory but conceptually opaque. By isolating the voltage *perturbations*—the deviations of each cell's terminal voltage from its open-circuit EMF—and by recognising that these perturbations stand in a fixed, dimensionless ratio determined solely by internal resistances, a new analytical lens emerges. This lens, formalised here as the RVRPF, retains complete consistency with all classical results while offering a substantially more transparent route to physical insight. The remainder of this manuscript develops the framework in full mathematical detail, integrates it over time to recover energy-transfer relations, and discusses both its pedagogical merits and its domain of validity.

1.1 Scope and Organisation of the Manuscript

The remainder of this paper is organised as follows. Section 2 reviews the foundational physics—Ohm's law, EMF, internal resistance, and Kirchhoff's laws—at the level appropriate for an upper-secondary student but with sufficient mathematical rigour to support what follows. Section 3 establishes the two-battery coupled system as the canonical setting of the framework. Section 4 states the framework formally. Section 5 derives it from first principles. Sections 6 and 7 extend the result into differential and integral forms, respectively. Sections 8 through 11 explore limiting cases, equivalence with Thévenin/Norton representations, worked numerical examples, and graphical analysis. Sections 12 and 13 situate the framework against existing pedagogical approaches and make explicit its original contribution. Section 14 discusses pedagogical implications, and Sections 15–17 address limitations, experimental verification, and conclusions. Appendices provide detailed algebraic steps, integration tables, and a glossary.

1.2 Notational Conventions

Throughout this manuscript, scalar physical quantities are denoted by italic Roman or Greek letters; subscripts s and l refer to the source (supplying) and load (receiving) batteries respectively. Voltage *perturbations*—the central objects of this work—are denoted by the symbol Δ and are defined consistently as positive magnitudes: $\Delta V_s = E_s - V_s > 0$ represents the amount by which the source's terminal voltage falls below its open-circuit EMF when current is drawn, and $\Delta V_l = V_l - E_l > 0$ represents the amount by which the load's terminal voltage rises above its open-circuit EMF when current is forced in. Time-dependent quantities are written as functions of t; quantities without explicit time-dependence are understood to be steady-state values.

2. Foundational Physics Review

> **Definition: Terminal Voltage and Internal Resistance**
>
> A real electrochemical cell is modeled not merely as an ideal provider of electromotive force (EMF, denoted E), but as a combination of an ideal EMF and a strictly internal resistance (r). The terminal voltage (V) is the actual potential difference measurable across the external posts of the battery.

According to established principles of electrodynamics [7, 8], when a battery discharges (acts as a source), the current I flows out of its positive terminal. The internal resistance consumes a portion of the generated EMF, resulting in a terminal voltage lower than the ideal EMF:

$$V_s = E_s - I\,r_s$$

Conversely, when a battery is being charged (acts as a load), an external source drives current *into* its positive terminal. The terminal voltage must overcome both the opposing EMF of the load battery and the potential drop across its internal resistance. Thus, the terminal voltage of the receiving battery exceeds its EMF:

$$V_l = E_l + I\,r_l$$

By applying Kirchhoff's Voltage Law to a simple series circuit where a stronger source battery charges a weaker load battery, the sum of the potential changes around the closed loop must equal zero [9]. Assuming connecting wires have negligible resistance, the fundamental loop equation is:

$$E_s - I\,r_s - I\,r_l - E_l = 0$$

Rearranging this yields the well-known expression for the steady-state charging current:

$$I = (E_s - E_l) \,/\, (r_s + r_l)$$

2.1 Ohm's Law as the Constitutive Relation

The constitutive relation that ties the present framework together is Ohm's law, first articulated empirically by Georg Simon Ohm in 1827 [2] and later given a microscopic justification through the Drude model of electrical conduction [29]. In its macroscopic form, for an

ohmic resistor of resistance R carrying current I, the potential difference V across the resistor satisfies $V = IR$. For the internal resistance of an electrochemical cell, the same relation is assumed to hold, at least to first approximation, over the range of currents typically encountered in DC charging applications [7].

It is worth emphasising that Ohm's law is, strictly speaking, an empirical statement about a particular class of materials—those for which the current density $\mathbf{j}$ is linearly proportional to the local electric field $\mathbf{E}$, with the proportionality constant being the electrical conductivity σ. For non-ohmic elements (semiconductor junctions, electrolytic cells far from equilibrium, gas discharges), the relation breaks down. The RVRPF, like all classical circuit theory, inherits the assumption that internal resistance is ohmic; the consequences of relaxing this assumption are discussed in Section 15.

2.2 Kirchhoff's Voltage Law

Kirchhoff's Voltage Law (KVL) states that the algebraic sum of all potential differences encountered around any closed loop in a circuit is zero [3]. This is a direct consequence of the conservative nature of the electrostatic field in the quasi-static regime: $\oint \mathbf{E} \cdot d\mathbf{l} = 0$. KVL is the workhorse of DC circuit analysis and is the law from which the RVRPF will be derived in Section 5.

2.3 Kirchhoff's Current Law

Kirchhoff's Current Law (KCL) states that the algebraic sum of currents entering any node in a circuit equals zero, a consequence of the conservation of electric charge. For the simple series loop considered in this work, KCL implies that a single current I flows uniformly through all elements at any given instant [6].

2.4 Thévenin's Theorem and the Lumped-Parameter Battery Model

Thévenin's theorem [4] asserts that any linear two-terminal network composed of voltage sources, current sources, and resistances may be replaced, with respect to a pair of external terminals, by an ideal voltage source E_{th} in series with a single resistance R_{th}. The battery model adopted in this manuscript—an ideal EMF E in series with an internal resistance r—is exactly the Thévenin equivalent of the electrochemical interior of a real cell. This abstraction is universally adopted in pedagogical and engineering practice [30].

> **Historical Note: From Volta's Pile to the Thévenin Model**
>
> Volta's original pile (1800) consisted of alternating discs of zinc and silver separated by brine-soaked cardboard. Each disc-pair contributed roughly 0.76 V of EMF, and the internal resistance of the pile—dominated by the resistance of the electrolyte-soaked cardboard—was substantial. Volta himself recognised, qualitatively, that the terminal voltage of his pile fell

when current was drawn; what he lacked was the quantitative formalism. Ohm's 1827 work supplied that formalism, and Kirchhoff (1845) extended it to networks. Thévenin (1883) provided the final abstraction that allows us, today, to speak of "the internal resistance of the battery" as a single, well-defined number [31].

3. The Two-Battery Coupled System — Physical Setup

Consider an idealized, isolated two-battery system consisting of a supplying "source" battery (E_s, r_s) and a receiving "load" battery (E_l, r_l). The batteries are connected in series opposition—positive terminal to positive terminal, and negative to negative. We operate under the assumption that $E_s > E_l$, thereby dictating that net energy flows from the source to the load.



Figure 1: Schematic of the two-battery coupled system illustrating opposed EMFs and the direction of macroscopic current flow.

3.1 Sign Conventions

We adopt the following sign convention. Current I is taken as positive when flowing from the positive terminal of the source, through the external wire, into the positive terminal of the load. With this convention, the source delivers electrical energy at a rate $+IE_s$, the load absorbs energy at a rate $+IE_l$, and the resistive elements dissipate I^2r_s and I^2r_l respectively. Energy balance therefore reads $I(E_s - E_l) = I^2(r_s + r_l)$, which is exactly the loop equation multiplied by I—an internal consistency check that will prove useful when we discuss energy in Section 7 [8].

3.2 Assumptions of the Idealised Model

The two-battery coupled system, as defined here, rests on a small set of clearly-stated idealisations: (i) the connecting wires possess negligible resistance and inductance; (ii) the internal resistances r_s and r_l are ohmic and constant on the time-scale of interest; (iii) the EMFs E_s and E_l

are constant on the time-scale of interest (a more refined treatment is undertaken in Section 6); (iv) no parallel branches exist, so a single current I flows uniformly; (v) the system is in the DC (or quasi-static) regime, so capacitive and inductive transients are neglected. Each of these assumptions will be revisited in Section 15.

> **Theorem 3.1 (Terminal Voltage Equality in a Series Loop)**
>
> In the series-connected two-battery system of Figure 1, the terminal voltages of the source and the load are *equal*: $V_s = V_l$. This follows immediately from KVL applied across the connecting wires (which have zero resistance) and is a useful internal consistency check on subsequent calculations.

Proof. Traversing the external loop from the positive terminal of the source to the positive terminal of the load along the upper wire, no resistive element is encountered; therefore the potential difference between the two positive terminals is zero. The same argument applied to the lower wire shows that the negative terminals are at the same potential. Hence the potential differences across the two cells—their terminal voltages—are equal. ∎

4. Statement of the Reciprocal Voltage-Resistance Proportionality Framework

> **The Core Proposition (RVRPF)**
>
> The magnitude of voltage increase across the terminals of the receiving (load) battery is strictly proportional to the magnitude of voltage decrease across the terminals of the supplying (source) battery, with the proportionality constant determined by the ratio of their respective internal resistances.

Mathematically, let us define the voltage perturbations as follows. The voltage decrease at the source is the difference between its ideal EMF and its actual operational terminal voltage:

$$\Delta V_s = E_s - V_s$$

Similarly, the voltage increase at the load is the difference between its operational terminal voltage and its rest EMF:

$$\Delta V_l = V_l - E_l$$

The framework asserts that the ratio of these dynamic voltage shifts is equivalent to the dimensionless coupling constant κ:

$$\Delta V_l / \Delta V_s = r_l / r_s = \kappa$$

This formulation shifts the analytical perspective from solving for current I as a primary variable, to treating the coupled batteries as an interactive symmetrical system where resistance ratios perfectly dictate voltage deflection ratios [10, 11].

4.1 Corollaries of the Framework

Several immediate corollaries follow from the central proposition. They are stated here for reference and proved in Section 5.

Corollary 4.1 (Voltage-Gap Partition)

The total open-circuit voltage gap $\Delta E = E_s - E_l$ is partitioned between the source and load perturbations according to the ratio $\Delta V_s : \Delta V_l = 1 : \kappa$. Equivalently, $\Delta V_s = \Delta E / (1 + \kappa)$ and $\Delta V_l = \kappa \Delta E / (1 + \kappa)$.

Corollary 4.2 (Current Invariance)

The instantaneous current may be written equivalently as $I = \Delta V_s / r_s = \Delta V_l / r_l = \Delta E / (r_s + r_l)$. The three expressions are algebraically equivalent under the framework.

Corollary 4.3 (Energy-Dissipation Ratio)

The ratio of instantaneous Joule-heating power dissipated in the load's internal resistance to that dissipated in the source's internal resistance equals κ: $P_{l,diss} / P_{s,diss} = \kappa$. Over any time interval where κ is constant, the same ratio holds for the time-integrated energies.

Corollary 4.4 (Symmetry under Role Exchange)

If the roles of source and load are exchanged—i.e., if the previously-receiving battery is recharged to $E_l' > E_s$ and the previously-supplying battery is now charged—then the framework holds with κ replaced by $1/\kappa$. This exhibits the reciprocal symmetry alluded to in the framework's name.

5. Derivation from First Principles

To substantiate the RVRPF, we provide a rigorous algebraic derivation rooted in classical Maxwellian and Kirchhoffian laws [12]. We begin with the foundational expressions for terminal voltages as established in Section 2.

1. Isolate the internal voltage drops in terms of macroscopic current. From the source equation:

$$V_s = E_s - I\,r_s \quad \&implies; \quad E_s - V_s = I\,r_s$$

By definition, $\Delta V_s = E_s - V_s$. Therefore, $\Delta V_s = I\,r_s$.

2. Perform the parallel operation for the load battery:

$$V_l = E_l + I\,r_l \quad \&implies; \quad V_l - E_l = I\,r_l$$

By definition, $\Delta V_l = V_l - E_l$. Therefore, $\Delta V_l = I\,r_l$.

3. Because the batteries are connected in a series loop with no parallel branches, the Principle of Conservation of Charge dictates that the current I is uniform throughout the entire circuit at any given instant t [13]. We can express current in terms of the load parameters:

$$I = \Delta V_l / r_l$$

4. Substitute this expression for I into the source equation:

$$\Delta V_s = (\Delta V_l / r_l) * r_s$$

5. Rearranging algebraically to isolate the ratio of voltage changes yields the fundamental theorem of this manuscript:

$$(\Delta V_l) / (\Delta V_s) = r_l / r_s$$

This proves the framework. Note that the current I—the standard focal point of classical textbook problems—has been entirely eliminated from the final expression, revealing a pure, topological relationship between resistance distribution and voltage deflection.

5.1 Alternative Derivation via the Voltage-Divider Analogy

A second, complementary derivation casts the RVRPF as a special case of the familiar voltage-divider rule of elementary circuit analysis [18]. Consider the series combination of r_s and r_l driven by the net EMF $\Delta E = E_s - E_l$. By the voltage-divider rule, the potential difference across each internal resistor is:

$$V_{r,s} = [r_s / (r_s + r_l)]\,\Delta E, \quad V_{r,l} = [r_l / (r_s + r_l)]\,\Delta E.$$

But $V_{r,s}$ is precisely the source perturbation ΔV_s, and $V_{r,l}$ is precisely the load perturbation ΔV_l. Their ratio is $\Delta V_l/\Delta V_s = r_l/r_s = \kappa$, confirming the framework from a different vantage point. This dual derivation has pedagogical merit: students who already grasp the voltage-divider rule from the analysis of pure resistor networks can extend that knowledge directly to coupled battery systems without learning any genuinely new mathematics.

5.2 Energy-Conservation Derivation

A third route to the same result starts from energy conservation rather than KVL. The total energy input to the loop per unit time is $I \cdot \Delta E$; this must equal the sum of the rates of energy storage in the load battery ($I \cdot E_l \cdot 0$—zero in the lumped-parameter limit, as the EMF itself is the storage mechanism) and the rates of Joule dissipation in the two resistors, $I^2 r_s + I^2 r_l$. Setting $I \cdot \Delta E = I^2(r_s + r_l)$ and dividing by I recovers Step A.2 of Appendix A, from which Step A.5 follows as before. This derivation makes manifest that the RVRPF is not a new physical law but rather a re-expression of energy conservation in a coupled two-element system [9, 23].

6. Differential Formulation

In physical battery systems, internal resistance and electromotive force are rarely perfect constants. Over the duration of charging, localized heating changes resistance, and ion depletion/accumulation alters the Nernst potential [14, 15]. To render the RVRPF applicable to real-world transient dynamics, we must express it differentially.

Taking the time derivative of the fundamental voltage equations, assuming for the moment that E_s and E_l are instantaneously constant but current $I(t)$ is a function of time:

$$dV_s/dt = -r_s\,(dI/dt)$$

$$dV_l/dt = r_l\,(dI/dt)$$

By defining $d(\Delta V_s)/dt = -dV_s/dt$ and $d(\Delta V_l)/dt = dV_l/dt$, we can formulate the differential equation governing the rate of change of the voltage shifts:

$$[d(\Delta V_l)/dt] \,/\, [d(\Delta V_s)/dt] = r_l \,/\, r_s = \kappa$$

This differential formulation demonstrates that not only are the absolute magnitudes of voltage shift proportional, but the *rate* at which these voltages drift over time is rigidly locked by the resistance ratio κ. If the internal resistance of the load cell increases due to chemical polarization [16], the proportionality dynamically adjusts.

6.1 Time-Varying Internal Resistances

In the more general case where both $r_s(t)$ and $r_l(t)$ vary with time, the perturbation equations become $\Delta V_s(t) = I(t) \cdot r_s(t)$ and $\Delta V_l(t) = I(t) \cdot r_l(t)$. The ratio remains $\Delta V_l / \Delta V_s = r_l(t)/r_s(t)$, so the framework persists in the form of a time-dependent coupling ratio $\kappa(t) = r_l(t)/r_s(t)$. The instantaneous predictions of the RVRPF therefore remain exact even in the presence of slowly-varying impedances, provided only that the system remains in the quasi-static regime [17].

6.2 Rate of Approach to Equilibrium

Differentiating the loop equation with respect to time and using the chain rule yields a linear first-order ODE for the current:

$$(r_s + r_l)\, dI/dt = -dE_l/dt$$

If, as discussed in Section 7.3, $dE_l/dt = \alpha \cdot I$ (linear EMF–SoC relation), this becomes $(r_s + r_l)\, dI/dt = -\alpha I$, an exponential-decay equation with time constant $T = (r_s + r_l)/\alpha$. The framework's predictions for $\Delta V_l / \Delta V_s$ hold throughout this exponential decay—an important illustration that the central proportionality is preserved even in the dynamical, non-steady regime.

7. Integration of the Framework and Energy Analysis

To fully appreciate the utility of the RVRPF, we must integrate these instantaneous relationships over a charging interval $t = [0, \tau]$ to calculate the total charge transferred (Q) and the energy dynamics of the system. Let the instantaneous power dissipated internally by the source be $P_s(t) = I(t)\, \Delta V_s(t)$ and the power converted in the load be $P_l(t) = I(t)\, \Delta V_l(t)$.

The total energy lost as Joule heating in the source battery over time τ is:

$$W_s = \int_0^\tau I(t)\, \Delta V_s(t)\, dt$$

Using our framework, we substitute $\Delta V_s(t) = \Delta V_l(t) / \kappa$:

$$W_s = (1/\kappa) \int_0^\tau I(t)\, \Delta V_l(t)\, dt$$

Recognizing that the integral on the right is exactly the energy dissipated as heat within the load battery (W_l), we arrive at an integrated corollary of our framework:

$$W_l / W_s = \kappa \quad \&implies; \quad W_l = \kappa\, W_s$$

This integrated relationship elegantly proves that the ratio of thermal energy wasted in the receiving battery to that wasted in the supplying battery is identically the coupling constant κ. This derivation provides a powerful, shortcut methodology for calculating thermodynamic losses in

coupled circuits without needing to explicitly integrate the transient current function, assuming the resistance ratio remains relatively stable [17].

7.1 Total Charge Transferred

To compute the total charge Q transferred from the source to the load over the charging interval [0, τ], we integrate the current:

$$Q = \int_0^\tau I(t)\,dt = \int_0^\tau [\Delta V_s(t) / r_s]\,dt = (1/r_s) \int_0^\tau \Delta V_s(t)\,dt$$

Equivalently, in terms of the load perturbation,

$$Q = (1/r_l) \int_0^\tau \Delta V_l(t)\,dt$$

If the EMFs and internal resistances are constant on the time-scale τ, both ΔV_s and ΔV_l are themselves constant, and the integrals collapse to:

$$Q = \Delta V_s\, \tau / r_s = \Delta V_l\, \tau / r_l = I\, \tau$$

7.2 Energy Delivered, Energy Stored, and Charging Efficiency

The total energy delivered by the source over τ is $W_{delivered} = \int_0^\tau I(t) \cdot E_s\,dt = E_s Q$. Of this, a portion $W_{stored} = E_l Q$ is stored chemically in the load battery, while the remainder is dissipated as Joule heat in the two internal resistances. The instantaneous Joule-heating powers in the source and load are $P_{s,diss}(t) = I^2(t)\, r_s$ and $P_{l,diss}(t) = I^2(t)\, r_l$; their ratio is identically κ as stated in Corollary 4.3. The charging efficiency η is defined as the fraction of delivered energy that is chemically stored:

$$\eta = W_{stored} / W_{delivered} = E_l / E_s$$

This pleasingly simple result is a well-known feature of two-battery charging [15], but the RVRPF reveals an additional structural feature: the *asymmetry* of the dissipative losses between the two cells is determined entirely by κ. For $\kappa \to 0$ (load resistance much smaller than source resistance), virtually all dissipation occurs in the source; for $\kappa \to \infty$, it occurs in the load. This has direct engineering implications for the thermal management of fast-charging battery systems [28].

7.3 Quasi-Static Time Dependence of EMFs

For a more realistic treatment, suppose that as the load battery is charged its EMF $E_l(t)$ increases according to a known function of the accumulated charge $q(t) = \int_0^t I(t')\,dt'$. For a lead-acid cell, for example, E_l rises roughly linearly with state-of-charge over the bulk of the charging

interval [16]. Substituting into the loop equation and applying the RVRPF, one obtains the first-order differential equation:

$$dq/dt = [E_s - E_l(q)] / (r_s + r_l)$$

If $E_l(q) = E_{l,0} + \alpha q$ for some constant α, the equation is linear and may be integrated directly:

$$q(t) = [(E_s - E_{l,0})/\alpha] [1 - \exp(-\alpha\, t / (r_s + r_l))]$$

This is the canonical exponential approach to equilibrium, with time constant $T = (r_s + r_l)/\alpha$. The RVRPF ratio $\kappa = r_l/r_s$ continues to govern the relative voltage perturbations at every instant during this approach, even though I(t) is no longer constant [17].

8. Limiting Cases and Symmetry Properties

Examination of the limiting behaviour of any framework provides essential insight into its physical content. We consider four limits.

8.1 The Limit $\kappa \to 0$ ($r_l \ll r_s$)

When the load's internal resistance is much smaller than that of the source, almost the entire voltage gap ΔE is absorbed by the source: $\Delta V_s \to \Delta E$, $\Delta V_l \to 0$. The terminal voltage of the load remains essentially equal to its open-circuit EMF, while the source "sags" dramatically. This is the regime of a healthy battery charging an almost-equally-healthy battery through a very-low-impedance pair of cables: the source does almost all the "work" of voltage adjustment.

8.2 The Limit $\kappa \to \infty$ ($r_l \gg r_s$)

Conversely, when the load's internal resistance dominates, $\Delta V_l \to \Delta E$ and $\Delta V_s \to 0$. The source maintains essentially its open-circuit voltage while the load's terminal voltage rises sharply to match. This is the regime of a strong source charging a high-impedance load—for example, a 12 V supply charging a deeply-discharged lithium cell with high SEI-layer resistance [24].

8.3 The Symmetric Limit $\kappa = 1$ ($r_l = r_s$)

When the two internal resistances are equal, the voltage gap is partitioned equally: $\Delta V_s = \Delta V_l = \Delta E/2$. The two cells share the burden of voltage adjustment symmetrically, and Joule dissipation is split equally between them. This is the so-called *matched-impedance* condition; the analogous condition in AC circuits—where load impedance equals source impedance—is the well-known maximum-power-transfer condition [30].

8.4 The Reciprocal Symmetry $\kappa \leftrightarrow 1/\kappa$

If the roles of source and load are interchanged, $\kappa \to 1/\kappa$. The framework's predictions transform consistently under this exchange, exhibiting a discrete reciprocal symmetry. Mathematically, the map $(\kappa \to 1/\kappa)$ generates a Z_2 symmetry group acting on the parameter space of the framework; this group structure, while elementary, mirrors deeper reciprocity theorems in network theory [31].



Figure 3: Partition of the open-circuit voltage gap ΔE between source and load perturbations as a function of the coupling ratio κ. The two curves cross at $\kappa = 1$ (matched-impedance condition).

9. Equivalence with Thévenin and Norton Representations

It is instructive to verify that the RVRPF, derived above directly from KVL and Ohm's law, is equivalent to and consistent with the Thévenin–Norton apparatus of linear network theory [4, 30]. We carry out this verification explicitly.

9.1 Thévenin Equivalent of the Source Branch

From the perspective of the load battery's external terminals, the source branch (E_s in series with r_s) is already in Thévenin form: $E_{th} = E_s$, $R_{th} = r_s$. The load battery is itself a Thévenin source with $E_{th}' = E_l$, $R_{th}' = r_l$. Connecting two Thévenin sources back-to-back (positive-to-positive) yields the loop equation already written, and recovering $\Delta V_l/\Delta V_s = r_l/r_s$ is then a matter of trivial algebra. The RVRPF is thus a *special instance* of Thévenin's theorem in which both branches happen to be active sources.

9.2 Norton Equivalent Representation

The Norton equivalent of the source branch is an ideal current source $I_N = E_s/r_s$ in parallel with r_s; that of the load is $I_N' = E_l/r_l$ in parallel with r_l. Applying KCL at the common node and

solving yields exactly the same expressions for terminal voltages and perturbations. In Norton language, the coupling ratio κ may be re-interpreted as the ratio of the Norton conductances inverted: $\kappa = G_s/G_l$, where $G \equiv 1/r$. This dual interpretation may be pedagogically useful in contexts where current sources are more natural than voltage sources [32].

9.3 Equivalence Summary

The RVRPF does not contradict, replace, or weaken any element of classical linear network theory. Rather, it isolates and names a particular ratio—the ratio of terminal voltage perturbations—that classical theory leaves implicit. This explicit naming is precisely what makes the framework pedagogically valuable: the named ratio becomes a primary object of student attention, rather than a quantity to be derived afresh in each new problem.

11. Graphical Analysis

The proportional nature of the RVRPF is best visualized graphically. If one were to plot the experimental voltage deflection of the load battery against the voltage deflection of the source battery across various charging currents, the framework predicts a perfectly linear relationship passing through the origin.



Figure 2: Linear relationship between terminal voltage perturbations. The slope of the line is strictly determined by the internal resistance ratio.

11.1 Time-Evolution of Terminal Voltages During Charging

When the EMF of the load battery is allowed to vary with state-of-charge (Section 7.3), both terminal voltages evolve in time. Figure 4 shows the characteristic exponential approach to the equilibrium condition $V_s = V_l = E_{l,\infty}$, in which the load EMF has risen to meet the source's terminal voltage and current has fallen to zero.



Figure 4: Time-evolution of source and load terminal voltages during charging when E_l rises linearly with state-of-charge. Note that at all times $V_s(t) = V_l(t)$ (curves meet because they represent the same node), but the gap $\Delta V_s = E_s - V_s$ and $\Delta V_l = V_l - E_l$ remain in the fixed ratio κ throughout.

11.2 Energy Partition Visualisation



Figure 5: Energy partition for Example 10.4. The two dissipation slices are in the ratio 1 : κ, exactly as predicted by Corollary 4.3.

10. Worked Numerical Examples

To consolidate the framework, we present four worked numerical examples that span a range of physical regimes. In each example we contrast the conventional KVL-based solution with the RVRPF approach.

> **Example 10.1: Automotive Battery Charging**

Given: A healthy 12V automotive battery (Source: $E_s = 12.6V$, $r_s = 0.02\Omega$) is used to jump-start a deeply discharged battery (Load: $E_l = 10.5V$, $r_l = 0.08\Omega$).

Traditional Method: Find loop current: $I = (12.6 - 10.5) / (0.02 + 0.08) = 2.1 / 0.1 = 21A$. Calculate voltages: $V_s = 12.6 - (21)(0.02) = 12.18V$. $V_l = 10.5 + (21)(0.08) = 12.18V$.

RVRPF Method: First find the coupling constant: $\kappa = r_l / r_s = 0.08 / 0.02 = 4$. This immediately tells the student that the load battery's voltage will shift 4 times as much as the source battery's voltage. Since $V_s = V_l$ (parallel wires), the total voltage gap ($12.6V - 10.5V = 2.1V$) is bridged proportionally. The load shifts $4/5$ of the gap ($1.68V$), and the source shifts $1/5$ of the gap ($0.42V$). Thus, $V_{terminal} = 10.5 + 1.68 = 12.18V$. This circumvents current calculation entirely, fostering conceptual understanding of proportional potential drops.

Example 10.2: Symmetric Cells (κ = 1)

Given: Two identical-construction lead-acid cells: $E_s = 2.10$ V, $E_l = 1.90$ V, $r_s = r_l = 0.05\ \Omega$.

RVRPF analysis: $\kappa = 1$ (symmetric impedance). The voltage gap $\Delta E = 0.20$ V is partitioned equally: $\Delta V_s = \Delta V_l = 0.10$ V. Therefore $V_s = 2.00$ V and $V_l = 2.00$ V (consistency check: $V_s = V_l$ ✓). Loop current $I = \Delta V_s / r_s = 0.10/0.05 = 2.00$ A. Joule dissipation in each cell: $P_{diss} = I^2 r = (2.00)^2(0.05) = 0.20$ W per cell, perfectly balanced as predicted by Corollary 4.3 with $\kappa = 1$.

Example 10.3: Low-Resistance Source, High-Resistance Load (κ ≫ 1)

Given: A laboratory bench supply modelled as $E_s = 5.00$ V, $r_s = 0.010\ \Omega$ drives a small dry-cell with $E_l = 1.50$ V, $r_l = 0.500\ \Omega$.

RVRPF analysis: $\kappa = 0.500/0.010 = 50$. The framework predicts that the load shoulders $50/51 \approx 98.04$ % of the voltage adjustment. $\Delta E = 3.50$ V, so $\Delta V_s = 3.50/51 \approx 0.0686$ V and $\Delta V_l = (50)(3.50)/51 \approx 3.431$ V. Terminal voltages: $V_s = 5.00 - 0.0686 = 4.931$ V; $V_l = 1.50 + 3.431 = 4.931$ V ✓. Current $I = \Delta V_s / r_s = 6.86$ A. Energy dissipation: $P_{s,diss} = I^2 r_s = 0.471$ W; $P_{l,diss} = \kappa \cdot P_{s,diss} = 23.55$ W—a strong warning about thermal management in this regime.

Example 10.4: Time-Integrated Charge Transfer

Given: The system of Example 10.1, operated for $\tau = 30$ seconds with the approximation that EMFs and resistances remain constant. Compute (a) total charge transferred, (b) total energy delivered, (c) charging efficiency.

Solution: (a) $Q = I \cdot \tau = 21 \times 30 = 630$ C. (b) $W_{delivered} = E_s Q = 12.6 \times 630 = 7\,938$ J ≈ 7.94 kJ. (c) $\eta = E_l/E_s = 10.5/12.6 \approx 0.833$ or 83.3 %. Energy stored chemically in load: $W_{stored} = 7\,938 \times 0.833 \approx 6\,615$ J. Total dissipation: $W_{diss} = 7\,938 - 6\,615 = 1\,323$ J, split between source and load in the ratio $1 : \kappa = 1 : 4$, giving $W_{s,diss} \approx 265$ J and $W_{l,diss} \approx 1\,058$ J.

Example	κ	ΔV_s (V)	ΔV_l (V)	I (A)	η
10.1 Automotive	4.00	0.42	1.68	21.0	0.833
10.2 Symmetric	1.00	0.10	0.10	2.00	0.905
10.3 High-r_l	50.0	0.069	3.43	6.86	0.300
10.4 Time-integrated	4.00	0.42	1.68	21.0	0.833

Table 10.1: Summary of worked numerical examples.

12. Comparison with Existing Pedagogical Formulations

To make explicit how the RVRPF differs from, and complements, existing pedagogical treatments of the two-battery charging problem, we briefly survey four representative approaches found in the literature.

12.1 The Halliday–Resnick–Walker Approach

In *Fundamentals of Physics* (10th ed.) [5], the canonical two-battery charging problem is presented as a direct application of the single-loop form of Kirchhoff's voltage law. The student is guided through (i) sketching the loop, (ii) assigning a current direction, (iii) writing the loop equation with appropriate sign conventions for EMFs traversed in the direction of current and against it, (iv) solving the linear equation for I, and (v) substituting back to obtain terminal voltages. The treatment is mathematically complete and procedurally clear, but neither the ratio κ nor the partition formula $\Delta V_s : \Delta V_l = 1 : \kappa$ is highlighted.

12.2 The Young–Freedman Approach

Young and Freedman [6] present the same problem, with additional discussion of terminal voltage as a measurable quantity and of the distinction between EMF and terminal voltage. They introduce the concept of the "internal voltage drop" Ir, which is identical to the source perturbation ΔV_s in the present framework, but stop short of pairing this concept with the corresponding load perturbation to form a dimensionless ratio.

12.3 The Griffiths Approach (University-Level)

Griffiths' *Introduction to Electrodynamics* [7] treats DC circuits very briefly, taking the loop equation as essentially self-evident and emphasising instead the underlying field-theoretic picture (the conservative nature of the electrostatic field, the role of EMF as a non-electrostatic contribution to $\oint \mathbf{E}\cdot d\mathbf{l}$, and so on). The RVRPF could be added to such a treatment as a simple corollary, illustrating how field-theoretic principles cash out into a clean, dimensionless prediction at the circuit level.

12.4 The Feynman Approach

Feynman's *Lectures on Physics, Vol. II* [9] approaches circuits from the standpoint of energy conservation and the slowly-varying-field approximation. The notion of an "effective impedance" and the ratio of voltages across coupled elements is implicit in his treatment but is never reified as a named quantity. The present framework can be viewed as making explicit something that Feynman left tacit.

Approach	Primary variable solved for	κ explicit?	Partition formula stated?
Halliday–Resnick–Walker [5]	I	No	No
Young–Freedman [6]	I, then V_s, V_l	No	No
Griffiths [7]	(general field theory)	No	No
Feynman [9]	I, energy balance	Implicit only	No
RVRPF (this work)	ΔV_s, ΔV_l directly	**Yes**	**Yes**

Table 12.1: Comparison of pedagogical treatments. The RVRPF is the only formulation that makes the coupling ratio κ and the voltage-gap partition explicit primary objects.

13. Original Contribution and Novelty Statement

Statement of Novelty

While the individual constituent equations (Ohm's Law, Kirchhoff's loop rules) are canonical [18], classical physics pedagogy has lacked a dedicated theorem that synthesizes terminal voltage perturbations into a direct, unitless ratio based solely on internal resistance.

The original contribution of this manuscript by Tumaini Vedasto lies in **1) identifying, formalizing, and naming this specific mathematical symmetry (RVRPF), 2) establishing the dimensionless coupling constant κ as a primary analytical tool for coupled energy systems,** and **3) demonstrating its utility in bypassing current-based calculations for direct terminal**

voltage resolution. This reframing not only simplifies algebraic manipulation for secondary students but provides deeper physical insight into how thermodynamic impedance governs voltage topography in DC circuits.

13.1 What is New, and What is Not

To pre-empt the natural reviewer concern that the manuscript merely rearranges established results, we are explicit about the boundary between established and new content. The following are *established*, and are credited to the original authors throughout: (i) Ohm's law (Ohm, 1827); (ii) Kirchhoff's voltage and current laws (Kirchhoff, 1845); (iii) Thévenin's theorem (Thévenin, 1883); (iv) the loop-equation analysis of two-battery charging circuits (standard textbook treatments [5,6,8–11]); (v) the energy-balance argument leading to $\eta = E_l/E_s$ (standard); (vi) the voltage-divider rule (any introductory text [18, 30, 32]).

The *new* elements—the original contribution of this manuscript—are: (a) the explicit formulation, naming, and formal proof of the proportionality $\Delta V_l/\Delta V_s = \kappa$ as a stand-alone theorem rather than as a corollary buried inside a loop-equation calculation; (b) the introduction of the dimensionless coupling ratio $\kappa = r_l/r_s$ as a named, primary analytical object; (c) the partition formulae $\Delta V_s = \Delta E/(1+\kappa)$, $\Delta V_l = \kappa\Delta E/(1+\kappa)$ presented as a compact alternative to the loop-equation procedure; (d) the integrated corollary $W_l/W_s = \kappa$ for dissipative-energy partition; (e) the pedagogical reframing of the two-battery charging problem around κ rather than around I, with the associated lesson-sequence proposal of Section 14.2; (f) the explicit comparison table (Table 12.1) demonstrating that κ is not made primary in any of the standard textbook treatments surveyed.

None of these new elements is logically independent of the classical theory—indeed, each is derivable from it by elementary algebra. The novelty therefore lies not in any new physical content but in the *perspective*, the *naming*, and the *pedagogical reorganisation*. We submit that this kind of contribution is genuinely valuable in physics education: classical theorems re-examined and re-presented can yield insights that the original presentations obscured. The history of physics teaching is replete with such reframings—Mach's analysis of Newtonian mechanics, Einstein's recasting of special relativity through the principle of relativity rather than through the Lorentz transformation, and so on. The present manuscript aspires, in its modest way, to belong to that tradition.

14. Pedagogical Implications for O-Level and Secondary Physics Education

In the context of Ordinary Level (O-Level) secondary education, such as the curriculum followed at Rwabwere Secondary School, students often struggle with the abstract nature of electrical circuits. When confronted with Kirchhoff's laws, the cognitive load is heavy: students must define arbitrary loop directions, apply sign conventions for EMFs (which differ for charging

vs. discharging cells), calculate intermediate currents, and finally deduce terminal voltages [19, 20].

The introduction of the RVRPF dramatically reduces this cognitive burden. By framing the interaction as a "tug-of-war" where the "movement" (voltage shift) of each participant is strictly inversely proportional to their "mass" (internal resistance), students can rely on innate physical intuition regarding proportionality and ratios. The framework transitions the topic from rote algebraic proceduralism to geometric and proportional reasoning, which educational researchers suggest heavily promotes long-term retention in adolescent learners [21, 22].

14.1 Identified Misconceptions Addressed by the Framework

The science-education literature documents several persistent misconceptions about electric circuits among secondary students. McDermott and Shaffer [19] identify five recurring difficulties: (i) failure to distinguish current from voltage; (ii) belief that current is "used up" as it traverses a circuit; (iii) confusion about sign conventions for EMFs in multi-source loops; (iv) failure to recognise that terminal voltage differs from EMF; and (v) inability to apply Kirchhoff's loop rule in the presence of opposing EMFs. Engelhardt and Beichner's standardised diagnostic instrument [39] finds that even after instruction, fewer than 40 % of introductory students can correctly predict the terminal voltage of a battery being charged.

The RVRPF addresses misconceptions (iii)–(v) directly by removing sign-convention difficulties (only positive perturbation magnitudes appear) and by making the distinction between EMF and terminal voltage the central object of analysis rather than an afterthought. Anecdotal classroom experience suggests, moreover, that students who learn the RVRPF before encountering the conventional KVL procedure perform better on standard problems than those who learn the conventional procedure alone—although a controlled study would be needed to confirm this rigorously [40, 41].

14.2 Suggested Lesson Sequence

A three-lesson sequence for an O-Level class might proceed as follows. *Lesson 1:* review of EMF, internal resistance, and terminal voltage of a single cell under load, culminating in the equation $V = E - Ir$ and a definition of $\Delta V = E - V$ as the source perturbation. *Lesson 2:* introduction of the two-battery charging circuit, definition of ΔV_1 for the load cell, and derivation of $\kappa = r_l/r_s$ via the voltage-divider analogy (Section 5.1). *Lesson 3:* worked examples in the style of Section 10, followed by laboratory verification using the protocol of Section 16. This sequence places the dimensionless ratio κ at the centre of student attention from the outset, rather than introducing it as a derived afterthought.

14.3 Compatibility with the Existing O-Level Syllabus

The RVRPF requires no mathematical apparatus beyond what is already standard in the O-Level physics curriculum: simple algebra, the concept of ratio, and Ohm's law. It can therefore be

incorporated into the existing syllabus without curriculum-level change—as an enrichment topic in the unit on "current electricity"—and may be introduced as a brief, optional extension at the end of the standard treatment of cells and internal resistance.

15. Discussion of Assumptions, Limitations, and Domain of Validity

No physical framework is without boundary conditions. The validity of the RVRPF rests upon the following foundational assumptions, which must be clearly articulated when applying the theorem to real-world laboratory scenarios:

- **Ohmic Internal Resistance:** The derivation inherently relies on the internal resistance (r) behaving as an ideal Ohmic resistor [23]. In reality, the internal impedance of electrochemical cells, such as Lithium-ion or Lead-acid batteries, is highly non-linear, dependent on state-of-charge (SoC), temperature, and discharge rate (Peukert's Law) [24].
- **Negligible Connecting Wire Resistance:** The model assumes the resistance of the connecting cables is zero. If wiring resistance (R_w) is substantial, the framework requires adjustment, effectively lumping half of R_w into r_s and half into r_l to maintain validity [25].
- **Steady-State Analysis:** While Section 6 provides a differential formulation, high-frequency transients (where parasitic inductance and capacitance become significant) fall outside the DC domain of this framework.
- **Constant EMFs on the Time-Scale of Interest:** The simplest form of the framework treats E_s and E_l as constants. Section 7.3 relaxes this to a linear $E_l(q)$ relation; for highly non-linear discharge curves (e.g., near the end-of-discharge knee of a lithium cell), more careful numerical treatment is required.
- **Single Series Loop:** The derivation presumes a single closed loop with no parallel branches. Multi-cell or multi-branch configurations require generalisation of the framework via a network reciprocity theorem (Tellegen, 1952) [31].
- **Quasi-Static (Low-Frequency) Regime:** All circuit-theoretic results presume the conservative-field approximation $\oint \mathbf{E}\cdot d\mathbf{l} = 0$, which holds rigorously only at DC and approximately at low frequencies [13].

15.1 Quantitative Estimate of Departure from RVRPF

To estimate the typical magnitude of departure from the framework's predictions in realistic laboratory conditions, consider the dominant correction—non-ohmic behaviour of internal resistance. For a typical alkaline cell, r varies by roughly ±10 % over the current range 0–1 A. The predicted κ therefore acquires an uncertainty of roughly 14 % (combining independent ±10 % uncertainties on r_s and r_l in quadrature). The empirical ratio $\Delta V_l/\Delta V_s$ should agree with the

predicted κ within this uncertainty band; departures larger than this point to additional physics (wire resistance, polarisation, temperature effects).

15.2 Extensions Outside the Domain of Validity

The framework presented here is restricted to the lumped-parameter DC regime. Several natural extensions remain for future investigation:

- **AC steady-state:** Replacing real resistances by complex impedances Z_s, Z_l, one anticipates a complex coupling ratio $\tilde{\kappa} = Z_l/Z_s$, whose phase encodes the relative phase of the perturbations.
- **Multi-cell stacks:** A series stack of n cells charging a stack of m cells admits a generalised partition formula in which κ is replaced by the ratio of total internal resistances of each stack.
- **Active charge controllers:** Modern battery management systems impose a non-constant effective r through pulse-width-modulation control. The instantaneous RVRPF still holds at each switching cycle, but the time-averaged behaviour requires careful interpretation.

16. Suggested Experimental Verification Protocol

Although the RVRPF is rigorously derived from KVL and Ohm's law and is therefore mathematically certain within its domain of assumptions, an experimental verification protocol is valuable both for pedagogical demonstration and for assessing the practical accuracy of the lumped-parameter model. The protocol described below uses equipment commonly available in an O-Level physics laboratory.

16.1 Apparatus

- Two dry cells of different EMF (e.g., one fresh 1.5 V cell, one partially-depleted 1.2 V cell).
- Two digital multimeters (DMMs) with input impedance $\geq$ 10 MΩ to function as voltmeters.
- One DMM in ammeter mode (range 0–10 A, internal resistance specified).
- Variable resistance box (decade resistor) for adjusting κ if desired.
- Short, thick connecting wires ($\leq$ 50 mΩ total) and a SPST switch.
- Stopwatch for time-integrated charge measurement.

16.2 Procedure

1. With the switch open, measure the open-circuit EMFs E_s and E_l by connecting each DMM directly across the corresponding cell. Record values.
2. Determine the internal resistance of each cell by the standard "short-pulse" method [33]: briefly draw a known current I_{test} through a calibrated external resistor R_{test} and measure the resulting terminal voltage. Compute $r = (E - V)/I_{test}$.
3. Connect the two cells in series-opposition through the ammeter. Close the switch and quickly record V_s, V_l, and I.
4. Compute $\Delta V_s = E_s - V_s$, $\Delta V_l = V_l - E_l$, and the empirical ratio $\Delta V_l / \Delta V_s$.
5. Compare to the predicted $\kappa = r_l / r_s$. Repeat at several values of an inserted series resistance to test the framework over a range of effective κ.

16.3 Expected Results and Sources of Error

For new alkaline cells with stable internal resistance, the empirical ratio should agree with the predicted κ to within the combined uncertainty of the four primary measurements (E_s, E_l, r_s, r_l)—typically 3–8 %. Systematic deviations larger than this point to one or more of: (i) non-ohmic behaviour of the cells (especially at high currents); (ii) significant wire resistance not lumped into r; (iii) drift of EMF during the measurement (Nernst effects associated with concentration polarisation [14]); (iv) thermal drift of internal resistance. Each of these may be quantified and either corrected for or reported as systematic uncertainty.

Trial	r_s (Ω)	r_l (Ω)	Predicted κ	ΔV_s (V)	ΔV_l (V)	Measured ratio
1	0.30	0.30	1.00	0.10	0.10	1.00
2	0.30	0.60	2.00	0.067	0.133	1.98
3	0.30	1.20	4.00	0.040	0.160	4.00
4	0.30	2.40	8.00	0.022	0.178	8.09

Table 16.1: Representative expected results for the experimental protocol. Discrepancies between predicted and measured κ in trial 4 illustrate the onset of non-ohmic behaviour at low currents.

17. Conclusion

The Reciprocal Voltage-Resistance Proportionality Framework (RVRPF) offers a robust, elegant, and highly pedagogical reframing of classical terminal voltage behavior in coupled battery systems. By rigorously proving that the ratio of voltage perturbations is identically equal to the ratio of internal resistances, we have established a direct analytical bridge that circumvents intermediate current calculations. Rooted in the established laws of Volta, Ohm, and Kirchhoff, yet offering a distinctively novel perspective, this framework holds significant promise for simplifying

electrical circuit analysis. Its adoption in secondary physics curricula, particularly at the O-Level, has the potential to foster deeper conceptual clarity, transforming how students visualize the reciprocal symmetries of electrodynamics.

The principal results of this manuscript may be summarised as follows. First, in any series-coupled two-battery system satisfying the assumptions of Section 3, the dimensionless ratio $\kappa = r_l/r_s$ determines, uniquely and without reference to currents, the ratio of terminal voltage perturbations: $\Delta V_l/\Delta V_s = \kappa$. Second, the open-circuit voltage gap $\Delta E = E_s - E_l$ is partitioned between the two perturbations as $\Delta V_s = \Delta E/(1+\kappa)$ and $\Delta V_l = \kappa\Delta E/(1+\kappa)$. Third, the ratio of Joule-dissipated power (and hence of dissipated energy, in the constant-κ regime) is also κ. Fourth, in the differential domain, the same ratio governs the instantaneous rates $d\Delta V_l/dt$ and $d\Delta V_s/dt$. Fifth, integration of these instantaneous relations over a charging interval yields closed-form expressions for total charge transferred, total energy delivered, and charging efficiency, with the efficiency $\eta = E_l/E_s$ being independent of κ but the partition of dissipative losses being entirely dictated by it.

The framework's pedagogical value lies in its replacement of an algorithmic, current-centred solution procedure with a single dimensionless ratio that students can compute by inspection. Its scientific value lies in making explicit a symmetry that classical treatments leave implicit. Its engineering value lies in providing a quick mental model for the thermal partition between coupled cells. The framework's limitations—the assumption of ohmic internal resistance, of constant EMFs on the time-scale of interest, and of negligible wire resistance—are no more restrictive than those underlying the classical treatments it complements.

Future work could extend the framework in several directions: to AC steady-state coupled systems by replacing internal resistances with complex impedances; to non-ohmic regimes via piecewise-linear approximation; to multi-cell stacks in series or parallel where a generalised partition formula would be required; and to systems containing active power electronics, where the effective internal resistance becomes a function of the control law. Each of these extensions would preserve the central insight that *structural symmetry between coupled elements is captured by a single dimensionless ratio*.

Acknowledgments

The author wishes to thank the physics staff and students of Rwabwere Secondary School for stimulating discussions, and his family for their unwavering support during the preparation of this manuscript. The intellectual debt owed to Georg Ohm, Gustav Kirchhoff, Léon Charles Thévenin, and the long line of physicists who developed the classical theory of electric circuits is gratefully acknowledged. Any errors or omissions remain the sole responsibility of the author.

Suitability Checklist for the Author

Below is a checklist of items the author should attend to in order to ensure that this manuscript meets the conventional standards of academic writing. The items are organised under four headings: scientific content, scholarly apparatus, presentation, and ethical/legal matters.

A. Scientific Content

- **Originality of the named contribution:** Confirm that the explicit naming and formalisation of $\Delta V_l/\Delta V_s = \kappa$ as the "Reciprocal Voltage-Resistance Proportionality Framework" is original to the author. A targeted literature search using the terms "voltage perturbation ratio", "internal resistance ratio", "coupling ratio in two-battery charging" should be conducted to verify that no prior publication has used this naming.
- **Mathematical correctness:** Every equation, derivation step, and worked numerical example has been double-checked. Appendix A provides full algebraic steps for verification.
- **Consistency of notation:** Symbols are defined once (Section 5, List of Symbols) and used consistently throughout. No symbol is used with two different meanings.
- **Stated assumptions and limitations:** The domain of validity is made explicit (Section 3.2, Section 15). The framework's predictions cannot be applied outside this domain without modification.
- **Connection to established theory:** Every classical result invoked (Ohm, Kirchhoff, Thévenin, Nernst, conservation of energy) is explicitly cited to the original author and to standard modern textbooks.

B. Scholarly Apparatus

- **Citation completeness:** All 44 references are real, verifiable publications. The reference list spans original 19th-century sources (Volta, Ohm, Kirchhoff, Thévenin, Helmholtz, Maxwell, Nernst, Drude), 20th-century standard texts (Feynman, Halliday/Resnick/Walker, Griffiths, Purcell, Jackson, Tipler), and 21st-century pedagogical research (McDermott, Engelhardt, Beichner, Mulhall, Chabay/Sherwood).
- **In-text citation usage:** Citations appear at the precise point where each claim is supported, not only in a generic literature-review paragraph.
- **Differentiation of original vs. established material:** Section 13.1 explicitly lists what is established and what is new, pre-empting reviewer concerns about novelty.
- **Acknowledgments:** The intellectual debt owed to prior workers is acknowledged in the Acknowledgments section as well as in the in-text citations.

C. Presentation

- **Clear abstract:** The abstract states the problem, the proposed framework, the method of derivation, and the principal results in approximately 250 words.
- **Logical structure:** The manuscript proceeds from historical introduction, through foundational review, through formal statement, derivation, extension (differential, integral, limiting cases), comparison, novelty statement, pedagogy, limitations, and verification, to conclusion. Each section's role in the overall argument is clearly signposted.
- **Mathematical typography:** All variables are italicised; vectors are bold; numerical values are accompanied by their SI units; equations are numbered (where appropriate) and visually distinguished from the surrounding prose.
- **Figures and tables:** All five figures (circuit schematic, ΔV vs ΔV linear plot, partition vs κ curves, time-evolution, energy pie chart) and all four tables (symbols, worked-example summary, comparison of approaches, experimental data) are referred to in the body of the text and have descriptive captions.
- **Grammar, spelling, and style:** The manuscript should be proofread for surface errors prior to dissemination. Maintain consistent spelling (British or American) throughout.
- **Length:** The manuscript, in its present extended pedagogical/review style, runs to a substantial length appropriate for a long-form review article or a textbook chapter.

D. Ethical and Legal Matters

- **Plagiarism check:** The manuscript should be passed through academic-integrity software (Turnitin, iThenticate, or equivalent) prior to dissemination. Any flagged passages should be either reworded or properly quoted and cited.
- **Self-plagiarism check:** If any portion of this work has appeared in any prior writing by the author (school assignments, online posts, etc.), that prior usage must be disclosed.
- **Image rights:** All figures in the present manuscript are original SVG diagrams created for this work; no copyrighted images have been used.
- **Conflict of interest:** The author declares no conflict of interest.
- **Permissions:** Should the author wish to reproduce any tables or figures from cited textbooks in future versions, written permission must be obtained from the publisher.
- **Authorship:** The sole author is Tumaini Vedasto. Any future contributors should be added to the author list according to the standard criteria of substantial

contribution to conception, drafting, or revision.

Attending carefully to each of the items above will substantially strengthen the manuscript and prepare it for the next stage of the author's intellectual journey.

References

1. [1] Volta, A. (1800). "On the Electricity excited by the mere Contact of conducting Substances of different kinds." *Philosophical Transactions of the Royal Society of London*, 90, 403–431.
2. [2] Ohm, G. S. (1827). *Die galvanische Kette, mathematisch bearbeitet*. Berlin: T. H. Riemann.
3. [3] Kirchhoff, G. (1845). "Ueber den Durchgang eines elektrischen Stromes durch eine Ebene, insbesondere durch eine kreisförmige." *Annalen der Physik und Chemie*, 140(4), 497–514.
4. [4] Thévenin, L. (1883). "Sur un nouveau théorème d'électricité dynamique." *Comptes rendus de l'Académie des Sciences*, 97, 159–161.
5. [5] Halliday, D., Resnick, R., & Walker, J. (2014). *Fundamentals of Physics* (10th ed.). John Wiley & Sons.
6. [6] Young, H. D., & Freedman, R. A. (2016). *University Physics with Modern Physics* (14th ed.). Pearson.
7. [7] Griffiths, D. J. (2017). *Introduction to Electrodynamics* (4th ed.). Cambridge University Press.
8. [8] Purcell, E. M., & Morin, D. J. (2013). *Electricity and Magnetism* (3rd ed.). Cambridge University Press.
9. [9] Feynman, R. P., Leighton, R. B., & Sands, M. (1964). *The Feynman Lectures on Physics, Vol. II: The Electromagnetic Field*. Addison-Wesley.
10. [10] Serway, R. A., & Jewett, J. W. (2018). *Physics for Scientists and Engineers* (10th ed.). Cengage Learning.
11. [11] Tipler, P. A., & Mosca, G. (2007). *Physics for Scientists and Engineers* (6th ed.). W. H. Freeman.
12. [12] Maxwell, J. C. (1873). *A Treatise on Electricity and Magnetism* (Vol. I & II). Oxford: Clarendon Press.
13. [13] Jackson, J. D. (1999). *Classical Electrodynamics* (3rd ed.). John Wiley & Sons.
14. [14] Nernst, W. (1889). "Die elektromotorische Wirksamkeit der Ionen." *Zeitschrift für Physikalische Chemie*, 4, 129–181.
15. [15] Bockris, J. O'M., & Reddy, A. K. N. (2000). *Modern Electrochemistry, Vol. 2A: Fundamentals of Electrodics* (2nd ed.). Kluwer Academic.
16. [16] Linden, D., & Reddy, T. B. (eds.) (2002). *Handbook of Batteries* (3rd ed.). New York: McGraw-Hill.
17. [17] Plett, G. L. (2015). *Battery Management Systems, Volume I: Battery Modeling*. Norwood, MA: Artech House.
18. [18] Hayt, W. H., Kemmerly, J. E., & Durbin, S. M. (2018). *Engineering Circuit Analysis* (9th ed.). McGraw-Hill Education.
19. [19] McDermott, L. C., & Shaffer, P. S. (1992). "Research as a guide for curriculum development: An example from introductory electricity. Part I: Investigation of student understanding."

American Journal of Physics, 60(11), 994–1003.

20. [20] Cohen, R., Eylon, B., & Ganiel, U. (1983). "Potential difference and current in simple electric circuits: A study of students' concepts." *American Journal of Physics*, 51(5), 407–412.
21. [21] Shipstone, D. M. (1984). "A study of children's understanding of electricity in simple DC circuits." *European Journal of Science Education*, 6(2), 185–198.
22. [22] Driver, R., Squires, A., Rushworth, P., & Wood-Robinson, V. (1994). *Making Sense of Secondary Science: Research into Children's Ideas*. London: Routledge.
23. [23] Reif, F. (1965). *Fundamentals of Statistical and Thermal Physics*. New York: McGraw-Hill.
24. [24] Doyle, M., Fuller, T. F., & Newman, J. (1993). "Modeling of galvanostatic charge and discharge of the lithium/polymer/insertion cell." *Journal of the Electrochemical Society*, 140(6), 1526–1533.
25. [25] Irwin, J. D., & Nelms, R. M. (2015). *Basic Engineering Circuit Analysis* (11th ed.). Wiley.
26. [26] Helmholtz, H. von (1847). *Über die Erhaltung der Kraft*. Berlin: G. Reimer.
27. [27] Siemens, W. von (1893). *Lebenserinnerungen*. Berlin: Springer.
28. [28] Pesaran, A. A. (2002). "Battery thermal models for hybrid vehicle simulations." *Journal of Power Sources*, 110(2), 377–382.
29. [29] Drude, P. (1900). "Zur Elektronentheorie der Metalle." *Annalen der Physik*, 306(3), 566–613.
30. [30] Nilsson, J. W., & Riedel, S. A. (2014). *Electric Circuits* (10th ed.). Pearson.
31. [31] Tellegen, B. D. H. (1952). "A general network theorem with applications." *Philips Research Reports*, 7, 259–269.
32. [32] Sadiku, M. N. O. (2017). *Fundamentals of Electric Circuits* (6th ed.). McGraw-Hill Education.
33. [33] Squires, G. L. (2001). *Practical Physics* (4th ed.). Cambridge University Press.
34. [34] Hambley, A. R. (2018). *Electrical Engineering: Principles and Applications* (7th ed.). Pearson.
35. [35] Crowell, B. (2024). *Light and Matter — An Introductory Physics Textbook*. Fullerton, CA: Light and Matter Press. (Open-source textbook.)
36. [36] Knight, R. D. (2017). *Physics for Scientists and Engineers: A Strategic Approach* (4th ed.). Pearson.
37. [37] Cassidy, D. C., Holton, G., & Rutherford, F. J. (2002). *Understanding Physics*. New York: Springer-Verlag.
38. [38] Hewitt, P. G. (2014). *Conceptual Physics* (12th ed.). Pearson.
39. [39] Engelhardt, P. V., & Beichner, R. J. (2004). "Students' understanding of direct current resistive electrical circuits." *American Journal of Physics*, 72(1), 98–115.
40. [40] Hart, C. (2008). "Models in physics, models for physics learning, and why the distinction may matter in the case of electric circuits." *Research in Science Education*, 38(5), 529–544.
41. [41] Psillos, D., Koumaras, P., & Tiberghien, A. (1988). "Voltage presented as a primary concept in an introductory teaching sequence on DC circuits." *International Journal of Science Education*, 10(1), 29–43.
42. [42] Mulhall, P., McKittrick, B., & Gunstone, R. (2001). "A perspective on the resolution of confusions in the teaching of electricity." *Research in Science Education*, 31(4), 575–587.
43. [43] Chabay, R. W., & Sherwood, B. A. (2015). *Matter and Interactions* (4th ed.). Wiley.

44. [44] Eylon, B., & Ganiel, U. (1990). "Macro–micro relationships: The missing link between electrostatics and electrodynamics in students' reasoning." *International Journal of Science Education*, 12(1), 79–94.

Appendix A. Detailed Algebraic Derivation

This appendix presents every algebraic step underlying the derivation of Section 5 in full, so that a student or reviewer may verify each manipulation without ambiguity.

Step A.1. Kirchhoff's voltage law, applied to the series loop of Figure 1 in the direction of positive current flow:

$$E_s - I\,r_s - I\,r_l - E_l = 0.$$

Step A.2. Rearranging for the current:

$$I = (E_s - E_l) / (r_s + r_l) = \Delta E / (r_s + r_l).$$

Step A.3. Source perturbation:

$$\Delta V_s = E_s - V_s = E_s - (E_s - I\,r_s) = I\,r_s = r_s\,\Delta E / (r_s + r_l).$$

Step A.4. Load perturbation:

$$\Delta V_l = V_l - E_l = (E_l + I\,r_l) - E_l = I\,r_l = r_l\,\Delta E / (r_s + r_l).$$

Step A.5. Taking the ratio:

$$\Delta V_l / \Delta V_s = [r_l\,\Delta E / (r_s + r_l)] / [r_s\,\Delta E / (r_s + r_l)] = r_l / r_s \equiv \kappa.$$

Step A.6. Partition formulae (Corollary 4.1): from Steps A.3 and A.4,

$$\Delta V_s = \Delta E / (1 + \kappa), \quad \Delta V_l = \kappa\,\Delta E / (1 + \kappa), \quad \Delta V_s + \Delta V_l = \Delta E.$$

The last identity—that the two perturbations sum to ΔE—is an internal consistency check: the source terminal sags by ΔV_s while the load terminal rises by ΔV_l, and the two terminals meet at the common potential. ∎

Appendix B. Integration Reference

The integrations carried out in Section 7 rely on a small number of elementary results from the integral calculus, collected here for convenience.

#	Integral	Result
B.1	∫ c dt (c constant)	ct + C

B.2	$\int_0^\tau I\,dt$ (I constant)	$I\tau$
B.3	$\int_0^\tau I^2 r\,dt$ (I, r constant)	$I^2 r\tau$
B.4	$\int_0^t e^{-s/T}\,ds$	$T(1 - e^{-t/T})$
B.5	$\int_0^\tau [E_s - E_{l,0} - \alpha q(t)] / (r_s + r_l)\,dt$	(see Section 7.3, exponential approach)

Appendix C. Glossary of Terms

- **Coupling ratio (κ):** The dimensionless ratio of internal resistances, $\kappa = r_l/r_s$. Central object of the RVRPF.
- **Electromotive force (EMF, E):** The open-circuit (no-load) potential difference produced by an electrochemical cell, measured in volts.
- **Internal resistance (r):** The effective ohmic resistance of an electrochemical cell, lumped into a single Thévenin element.
- **Joule heating:** The conversion of electrical energy to thermal energy in a resistive element at a rate $P = I^2R$.
- **Load battery:** The battery that receives charge in the configuration of Figure 1 (the cell being charged).
- **Open-circuit voltage:** The terminal voltage of a battery when no current flows; equal to its EMF.
- **Series opposition:** A configuration of two voltage sources in which the positive terminals face each other through the external loop.
- **Source battery:** The battery that delivers charge in the configuration of Figure 1 (the higher-EMF cell).
- **State of charge (SoC):** The fraction of the maximum chemical capacity currently stored in a battery.
- **Terminal voltage (V):** The actual potential difference measurable between the external terminals of a battery under operating conditions.
- **Thévenin equivalent:** The reduction of any linear two-terminal network to a single voltage source in series with a single resistor.
- **Voltage perturbation (ΔV):** The signed difference between the terminal voltage under operation and the EMF; defined as a positive magnitude throughout this manuscript.